





# Professional Audio Components

## Quick Reference & Specification

Model	MM6	MM6H	MM6A	MM8A
Znom Ohms	4	4	4	4
Revc Ohms	3.2	3.2	3.2	3.2
Sd m2	0.01539	0.01539	0.01389	0.0243
Mmd g	8.7	9.2	8.4	12.74
Usable Range (Hz)	107	90	102	92
Min Power	50W	60W	70W	75W
Ideal RMS Range	100W-120W	120W-140W	140W-160W	150W-170W
Peak Power	240W	280W	320W	340
Mms g	9	9.4	8.6	13
Cms MM/N	0.24	0.33	0.28	0.23
Vas L	8.1	11	7.5	18.9
Resonant Frequency(Hz)	100-15K	90-15K	100-18K	90-15K
Qms	4.44	3.62	5.34	5.88
Qes	0.43	0.7	0.44	0.61
Qts	0.39	0.59	0.41	0.55
BL T*M	6.5	4.8	6.2	6.1
Sensitivity(dB)	95.6	92.6	94.5	92.4
No	2.29	1.1	1.78	2.36



**240**  
PEAK WATTS

**280**  
PEAK WATTS

**320**  
PEAK WATTS

**340**  
PEAK WATTS

Massive Audio, Inc. P.O. BOX 252004 Los Angeles, CA 90025 U.S.A. [www.massiveaudio.com](http://www.massiveaudio.com)



Engineered in U.S.A.